

Compatibiliteitslijst

Lichtbron: IL-C5M36

Trafo		1x IL-C5M36	2x IL-C5M36	3x IL-C5M36	4x IL-C5M36
Type	Omschrijving				
4351.00	IBL Tronic trafo 35-105 VA	✓	✗	✓	✓
036600	Gira Tronic trafo 20-70 VA	✓	✓	✗	✗
037100	Gira Tronic trafo 20-105 VA	✗	✓	✗	✗
HTM105	Osram Tronic trafo 35-105 VA	✓	✓	✓	✓
HTM150	Osram Tronic trafo 50-150 VA	✓	✓	✓	✓
SNT 40	Jung Tronic trafo 10-40 VA	✓	✓	✗	✗
SNT 70 F	Jung Tronic trafo 20-70 VA	✓	✓	✓	✓
SNTF 105-35-3SW	Jung Tronic trafo 35-105 VA	✗	✗	✗	✗
TE105 S	HEP Tronic trafo 20-105 VA	✓	✓	✓	✓
320-0002	Niko Magnetische trafo max. 50 VA	✓	✓	✓	✓
320-00101	Niko Tronic trafo 20-70 VA	✓	✓	✓	✗
320-00107	Niko Tronic trafo 35-105 VA	✓	✗	✗	✗
Primaline 70	Phillips Tronic trafo 20-70 VA	✓	✓	✗	✗
Primaline 105	Philips Tronic trafo 35-105 VA	✓	✗	✗	✗
Primaline 150	Philips Tronic trafo 50-105 VA	✓	✓	✓	✓
	ATCO TO05-2 50W	✓	✓	✓	✓
	ATCO TEK-150 30-150W	✗	✗	✗	✗
	FN Light 20-105W	✓	✓	✓	✓
	POWER LIGHT 2x50W	✓	✓	✓	✓
	Rio 20-50W	✓	✓	✓	✓
	VIPER Tridonic 105VA	✗	✗	✗	✗
	VIPER 60VA	✗	✗	✗	✗